# Secrecy Rate Optimization for Secure Multicast Communications

Kanapathippillai Cumanan, Member, IEEE, Zhiguo Ding, Senior Member, IEEE, Mai Xu, Member, IEEE, and H. Vincent Poor, Fellow, IEEE

Abstract—Recently, physical layer security has been recognized as a new design paradigm to provide security in wireless networks. In contrast to the existing conventional cryptographic methods, physical layer security exploits the dynamics of fading channels to enhance security of wireless communications. This paper studies optimization frameworks for a multicasting network in which a transmitter broadcasts the same information to a group of legitimate users in the presence of multiple eavesdroppers. In particular, power minimization and secrecy rate maximization problems are investigated for a multicasting secrecy network. First, the power minimization problem is solved for different numbers of legitimate users and eavesdroppers. Next, the secrecy rate maximization problem is investigated with the help of private jammers to improve the achievable secrecy rates through a game theoretic approach. These jammers charge the transmitter for their jamming services based on the amount of interference caused to the eavesdroppers. For a fixed interference price scenario, a closed-form solution for the optimal interference requirement to maximize the revenue of the transmitter is derived. This rate maximization problem for a nonfixed interference price scenario is formulated as a Stackelberg game in which the jammers and transmitter are the leaders and follower, respectively. For the proposed game, a Stackelberg equilibrium is derived to maximize the revenues of both the transmitter and the private jammers. To support the derived theoretical results, simulation results are provided with different numbers of legitimate users and eavesdroppers. In addition, these results show that physical layer security based jamming schemes could be incorporated in emerging and future wireless networks to enhance the quality of secure communications.

*Index Terms*—Convex optimization, game theory, multicasting network, physical layer security.

Manuscript received January 21, 2016; revised June 7, 2016; accepted July 10, 2016. Date of publication August 16, 2016; date of current version November 16, 2016. The work of K. Cumanan and Z. Ding was supported by H2020-MSCARISE-2015 under Grant 690750. The work of Z. Ding was supported in part by the Royal Society International Exchange Scheme and in part by the U.K. EPSRC under Grant EP/N005597/1. The work of M. Xu was supported in part by the NSFC project under Grant 151061. The work of H. V. Poor was supported by the U.S National Science Foundation under Grant CMMI-1435778. The guest editor coordinating the review of this manuscript and approving it for publication was Prof. Shrikanth Narayanan. (*Corresponding author: Mai Xu*.)

K. Cumanan is with the Department of Electronics, University of York, York YO10 5DD, U.K. (e-mail: kanapathippillai.cumanan@york.ac.uk).

Z. Ding is with the School of Computing and Communications, Lancaster University Lancaster, Bailrigg LA1 4WA, U.K. (e-mail: z.ding@lancaster. ac.uk).

M. Xu is with the School of Electronic and Information Engineering, Beihang University, Beijing 100191, China (e-mail: MaiXu@buaa.edu.cn).

H. V. Poor is with the Department of Electrical Engineering, Princeton University, Princeton, NJ 08544 USA (e-mail: poor@princeton.edu).

Color versions of one or more of the figures in this paper are available online at http://ieeexplore.ieee.org.

Digital Object Identifier 10.1109/JSTSP.2016.2600518

## I. INTRODUCTION

I N traditional wireless networks, security is achieved in the upper layers based on conventional cryptographic methods. However, some emerging networking paradigms present challenges in terms of key exchange and distribution. Recently, physical layer based secret communication has received considerable attention due to its suitability for dynamic network configurations and distributed processing techniques [1]–[3]. In addition, this approach implements security in the physical layer as a complement to the cryptographic methods by exploiting channel state information (CSI) of legitimate parties as well as eavesdroppers.

The ideas behind physical layer security were first investigated in [4] and [5] based on information theoretic concepts by defining the secrecy capacity of wiretap and related channels. Recently, multiantenna secrecy channels have received considerable attention in the research community since the use of multiple antennas yields spatial diversity and additional secrecy degrees of freedom [6]-[14]. In [6], the secrecy capacity of multiple-antenna wiretap channels was presented under an average power constraint, whereas the same secrecy capacity was established in [7] as the saddle point solution to a min-max problem. A transmit covariance matrix design was considered in [8] to maximize the ergodic secrecy rate with a power constraint for a multiple-input single-output (MISO) wiretap channel model, whereas an optimal transmit design through the semidefinite programming approach is proposed in [9] for the same channel model as in [8]. In [10], full rank solutions have been derived for the multiple-input multiple-output (MIMO) wiretap channel with an average power constraint and an alternative solution based on Taylor series has been proposed for the same problem in [11].

Cooperative jamming is a well known approach to further improve secrecy rates, in which the jamming signals are introduced at the eavesdropper with the help of relays or jamming nodes [15]–[20]. This scheme degrades the eavesdropper's capability of retrieving the information intended for the legitimate users. The achievable rates and an efficient cooperative jamming protocol have been presented for the general Gaussian multiple access and two-way wiretap channels in [15]. In [16], different cooperative jamming strategies have been developed for two-hop relay networks to confuse eavesdroppers with the assumption of global CSI. Opportunistic relaying for secret communications has been presented in [17] through cooperative jamming and relay chatting, whereas full-duplex jamming and optimal cooperative jamming for relays have been proposed in [18]–[20], respectively. On the other hand, jamming signals

1932-4553 © 2016 IEEE. Personal use is permitted, but republication/redistribution requires IEEE permission. See http://www.ieee.org/publications\_standards/publications/rights/index.html for more information.



Fig. 1. A multicasting secrecy network in the presence of multiple eavesdroppers.

can be embedded in the transmitted signal from the legitimate transmitter to confuse the eavesdroppers, a strategy known as the artificial noise (AN) technique in the literature [21]–[23]. In [21], a more general framework of AN methods has been presented for multi-antenna nodes. An AN scheme based on spatial selection has been proposed for MISO multi-evesdropper secrecy rate maximization in [22] and a quality of service based beamforming scheme is has been proposed in [23] to employ AN.

Recently, game theoretic techniques have been incorporated into the study of secure wireless communications for decision making and resource allocation, e.g., [24]-[30]. In [24], a novel cooperative paradigm has been proposed to improve the secrecy of primary users with the help of the secondary users in cognitive radio networks through a Stackelberg game approach. Secure games have been formulated for a secret communication network with an unfriendly jammer through a non-cooperative zero-sum continuous game in [25]. Physical layer security has also been investigated in a two way untrusted relay system through a Stackelberg game in [26]. In [27], a game theoretic framework has been developed for multi-hop networks in the presence of eavesdroppers. Transmission strategies have been proposed for MIMO secret communication networks in the presence of a multi-antenna eavesdropper through game theoretic approaches in [28], whereas a secrecy game for a Gaussian MISO interference channel has been investigated in [29].

In this paper, we consider a secure multicasting network as shown in Fig. 1 where a transmitter broadcasts the same information to multiple legitimate users. To the best of the authors' knowledge, only a few works have investigated multicasting secrecy networks with multiple eavesdroppers. In [31], multicasting secrecy rate maximization was investigated for MISO channels with multiple eavesdroppers equipped with multiple antennas based on convex approximation techniques, whereas performance analysis has been derived for a secure multicasting network consisting of a single-antenna transmitter with multiple multi-antenna receivers as well as multiple multi-antenna eavesdroppers in [32]. In [33], a multicarrier based physical layer security scheme has been investigated for multicasting systems and a waveform design has been proposed for secure singleinput single-output multicasting transmission in [34]. Recently, different capacities have been derived for secure multicasting



Fig. 2. A multicasting secrecy network with multiple legitimate users, multiple eavesdroppers and private jammers.

in stochastic MIMO networks, whereas a joint beamforming and user selection scheme has been proposed for MISO wiretap channels with multiple single-antenna eavesdroppers in [35]. However, secure multicasting communications with cooperative jamming has not been considered in these works. In this paper, we propose secrecy rate optimization frameworks with cooperative jamming, in which a game theoretic approach is used to derive the optimal strategies of the legitimate transmitter and the jammers. The contributions of this paper are summarized as follows:

- 1) *Power minimization*: We consider a beamforming design for a secure communication network consisting of a legitimate user and an eavesdropper, where our goal is to minimize the transmit power with a secrecy rate constraint. This problem can be easily formulated as a second order cone programming (SOCP) problem. Furthermore, we derive a closed-form optimal solution based on the dual problem and Karush-Kuhn-Tucker (KKT) conditions. The derived optimal solution is validated through a comparison with the SOCP results via simulations. Next, the power minimization problem is considered for a scenario with multiple legitimate users and multiple eavesdroppers. This problem is not convex in terms of the beamformer at the transmitter. However, we formulate this problem as a semidefinite programming problem by introducing a new variable and also using semidefinite relaxation.
- 2) Game theory based secrecy rate maximization: In the above power minimization schemes, the legitimate transmitter requires a certain amount of transmit power to satisfy the required secrecy rates. However, it is not always possible to realize the predefined secrecy rates, either because the available transmit power is limited or because it might be expensive to use the required amount of power. To overcome these issues, external jammers can be employed to introduce interference to the eavesdroppers, which will improve the achievable secrecy rate at the legitimate users. Therefore, we consider a multicasting secrecy network with multiple legitimate users and multiple eavesdroppers as shown in Fig. 2 in which private jammers introduce interference to the eavesdroppers.

Particularly, these private jammers charge the transmitter for their jamming service based on the amount of interference caused at the eavesdroppers. On the other hand, the legitimate users also pay the transmitter according to their achieved secrecy rates, which provides a profit to the transmitter and compensates for the charges of the private jammers. Based on the revenues at both the transmitter and the private jammers, we formulate this problem as a Stackelberg game in which the private jammers and the transmitter are the *leaders* and the *follower*, respectively. For the proposed game, we derive a Stackelberg equilibrium solution with different numbers of legitimate users and eavesdroppers, which maximizes the revenues of the transmitter and the private jammers.

The remainder of the paper is organized as follows. The system model is described in Section II. Section III presents the power minimization problem with different numbers of legitimate users and eavesdroppers. The Stackelberg game is introduced in Section IV, whereas Stackelberg equilibrium solutions are derived for the proposed game in Section V for different scenarios. Section VI provides simulation results to support the theoretical results. Finally, Section VII concludes the paper.

# A. Notation

We use uppercase boldface letters for matrices and lowercase boldface letters for vectors.  $(\cdot)^H$  denotes conjugate transpose. Tr $(\cdot)$  and  $\mathbb{E}\{\cdot\}$  stand for the trace of a matrix and the expectation of a random variable.  $\mathbf{A} \succeq \mathbf{0}$  indicates that  $\mathbf{A}$  is a positive semidefinite matrix. I denotes the identity matrix of appropriate size.  $\|\cdot\|_2$  represents the Euclidean norm of a matrix.  $[x]^+$ denotes max $\{x, 0\}$ .

## II. SYSTEM MODEL

We consider a multicasting secrecy network with K legitimate users and L eavesdroppers as shown in Fig. 1, where a transmitter broadcasts the same information to all the legitimate users in the presence of multiple eavesdroppers. It is assumed that the transmitter is equipped with  $N_T$  transmit antennas, whereas each of the legitimate users and the eavesdroppers has a single receive antenna. The channel coefficients between the legitimate transmitter and the  $k^{th}$  legitimate user and between the legitimate transmitter and  $l^{\text{th}}$  eavesdropper are denoted by  $\mathbf{h}_k \in \mathbb{C}^{N_T \times 1}$  and  $\mathbf{g}_l \in \mathbb{C}^{N_T \times 1}$ , respectively. Here, it is assumed that the transmitter has perfect CSI of the legitimate users and the eavesdroppers. This assumption is appropriate for the multicasting network being considered here, in which potential eavesdroppers are also legitimate members of the network, but do not have the permission to receive particular multicast content being protected. This assumption has been widely used in the literature [2], [16], [19], [23], [36]–[41]. The noise powers at the  $k^{\text{th}}$ legitimate user and the eavesdroppers are assumed to be  $\sigma_k^2$  and  $\sigma_e^2$ , respectively. The received signals at the  $k^{\rm th}$  legitimate user and  $l^{\text{th}}$  eavesdropper can be written as follows:

$$y_k = \mathbf{h}_k^H \mathbf{w} s + n_k, \ y_l = \mathbf{g}_l^H \mathbf{w} s + n_l, \tag{1}$$

where  $s (\mathbb{E}\{s^2\} = 1)$ , and  $\mathbf{w} \in \mathbb{C}^{N_T \times 1}$  are the signal intended to the legitimate users and the beamformer at the legitimate transmitter, respectively.  $n_k$  and  $n_l$  denote the noise at the  $k^{\text{th}}$ legitimate user and  $l^{\text{th}}$  eavesdropper, respectively. Assuming additive white Gaussian noise, the achievable secrecy rate at the  $k^{\text{th}}$  legitimate user is given by [7]

$$R_k = \left[ \log \left( 1 + \frac{\mathbf{w}^H \mathbf{h}_k \mathbf{h}_k^H \mathbf{w}}{\sigma_k^2} \right) - \max_{1 \le l \le L} \log \left( 1 + \frac{\mathbf{w}^H \mathbf{g}_l \mathbf{g}_l^H \mathbf{w}}{\sigma_e^2} \right) \right]^+.$$

#### **III. SECRECY RATE OPTIMIZATIONS**

In this section, we consider the power minimization problem for a multicasting secrecy network in which the transmitter provides the required secrecy rates for all the legitimate users in the presence of multiple active eavesdroppers. This problem can be formulated as an optimization framework in which the total transmit power is minimized to satisfy the secrecy rate constraints.

## A. Power Minimization

First, the power minimization problem is investigated with a single legitimate user and an eavesdropper. For this problem, a closed-form optimal solution can be derived based on the dual problem and KKT conditions. For the scenario of multiple legitimate users in the presence of multiple eavesdroppers, it is formulated into a semidefinite programming framework through semidefinite relaxation.

A. Single Legitimate User and Single Eavesdropper: With a single legitimate user and a single eavesdropper, the power minimization problem can be formulated with the secrecy rate constraint as follows:

$$\min_{\mathbf{w}} \|\mathbf{w}\|_{2}^{2}$$
s.t.  $\log\left(1 + \frac{\mathbf{w}^{H}\mathbf{h}_{1}\mathbf{h}_{1}^{H}\mathbf{w}}{\sigma_{1}^{2}}\right) - \log\left(1 + \frac{\mathbf{w}^{H}\mathbf{g}_{1}\mathbf{g}_{1}^{H}\mathbf{w}}{\sigma_{e}^{2}}\right) \geq \bar{R}_{s},$  (2)

where  $\mathbf{h}_1$  and  $\mathbf{g}_1$  are the channels between the legitimate transmitter and legitimate user and between the legitimate transmitter and the eavesdropper, respectively. In addition,  $\bar{R}_s$  is the required secrecy rate of the legitimate user. The problem in (2) can be formulated into an SOCP problem. However, we derive a closed-form optimal solution based on the dual problem and KKT conditions. In the simulation section, we validate this closed-form solution by comparing it with SOCP results.

Lemma 1: The optimal solution of (2) is given by

$$\mathbf{w}^{*} = \sqrt{p^{*}} \mathbf{\tilde{w}}^{*}, \ \mathbf{\tilde{w}}^{*} = \frac{\mathbf{w}_{1}}{\|\mathbf{w}_{1}\|_{2}}, \mathbf{w}_{1} = v_{\max} \left( \mathbf{\hat{h}}_{1} \mathbf{\hat{h}}_{1}^{H} - 2^{\bar{R}_{s}} \mathbf{\hat{g}}_{1} \mathbf{\hat{g}}_{1}^{H} \right)$$
$$p^{*} = \lambda_{s}^{*} \left( 2^{\bar{R}_{s}} - 1 \right), \lambda_{s}^{*} = \frac{1}{\lambda_{\max} \left( \mathbf{\hat{h}}_{1} \mathbf{\hat{h}}_{1}^{H} - 2^{\bar{R}_{s}} \mathbf{\hat{g}}_{1} \mathbf{\hat{g}}_{1}^{H} \right)}, \quad (3)$$

where  $\hat{\mathbf{h}}_1 = \frac{\mathbf{h}_1}{\sigma_1}$ ,  $\hat{\mathbf{g}}_1 = \frac{\mathbf{g}_1}{\sigma_e}$  and  $\lambda_{\max}(\cdot)$ ,  $v_{\max}(\cdot)$  denote the maximum eigenvalue and the eigenvector corresponding to the maximum eigenvalue, respectively.

*Proof:* Please refer to Appendix A.

A. Multiple Legitimate Users and Multiple Eavesdroppers: The power minimization problem with multiple legitimate users and multiple eavesdroppers can be formulated as

$$\begin{split} \min_{\mathbf{w}} \|\mathbf{w}\|_{2}^{2} \\ \text{s.t.} \log \left(1 + \frac{\mathbf{w}^{H} \mathbf{h}_{k} \mathbf{h}_{k}^{H} \mathbf{w}}{\sigma_{k}^{2}}\right) &- \max_{1 \leq l \leq L} \log \left(1 + \frac{\mathbf{w}^{H} \mathbf{g}_{l} \mathbf{g}_{l}^{H} \mathbf{w}}{\sigma_{e}^{2}}\right) \\ \geq \bar{R}_{k}, \\ k = 1, \cdots, K, \ l = 1, \cdots, L, \end{split}$$
(4)

where  $\bar{R}_k$  is the target secrecy rate of the  $k^{\text{th}}$  legitimate user. This problem is not convex in terms of the transmit beamformer. However, by introducing a new semidefinite matrix  $\mathbf{W} = \mathbf{w}\mathbf{w}^H$ and relaxing the rank-one constraint, the above problem can be formulated into a semidefinite programming (semidefinite relaxation problem) as follows:

$$\min_{\mathbf{W} \succeq \mathbf{0}} \quad \operatorname{Tr}\{\mathbf{W}\}$$
s.t.  $1 + \operatorname{Tr}\{\tilde{\mathbf{h}}_{k}\tilde{\mathbf{h}}_{k}^{H}\mathbf{W}\} - 2^{\bar{R}_{k}}\operatorname{Tr}\{\tilde{\mathbf{g}}_{l}\tilde{\mathbf{g}}_{l}^{H}\mathbf{W}\} \ge 2^{\bar{R}_{k}},$ 

$$k = 1, \cdots, K, \quad l = 1, \cdots, L,$$

$$(5)$$

where  $\tilde{\mathbf{h}}_k = \frac{\mathbf{h}_k}{\sigma_k}$  and  $\tilde{\mathbf{g}}_l = \frac{\mathbf{g}_l}{\sigma_e}$ . If the solution of the above problem is rank-one, then it will be the optimal solution of the original problem in (4). In case of a non-rank-one solution, randomization techniques can be used to construct a rank-one solution from the non-rank-one solution of (5) [42], [43].

## IV. GAME THEORY BASED SECRECY RATE OPTIMIZATION

In order to satisfy the target secrecy rates, the transmitter requires a certain amount of transmit power. However, it is not always possible to provide the target secrecy rates due to limited transmit power or because it might require a significant amount of transmit power which will be infeasible in terms of hardware implementations at the transmitter. On the other hand, in multicasting networks, it is difficult to achieve the target secrecy rates at different legitimate users with a single beamformer. To overcome these issues, cooperative jamming would be a solution, which will enhance the secrecy performance at the legitimate users. Here, we consider a multicasting secrecy network in which a set of private (friendly) jammers are employed to provide jamming services as shown in Fig. 2. These private jammers introduce interference to the eavesdroppers who overhear the multicasting transmission from the transmitter. In addition, these jammers ensure that there is no interference leakage to the legitimate users, which could be achieved by appropriately designing the beamformers at the jammers and employing a dedicated jammer near to each eavesdropper. Since, a dedicated jammer is located close to the corresponding eavesdropper, each eavesdropper receives interference only from the corresponding private jammer.<sup>1</sup> These private jammers charge the transmitter for their dedicated jamming service based on the amount of interference caused to each eavesdropper. To compensate for these interference prices, the legitimate transmitter also introduces charges to the legitimate users for its enhanced secured service based on the achieved secrecy rates. For this scenario, we consider secrecy rate maximization with multiple legitimate users, multiple eavesdroppers and multiple corresponding jammers. We formulate this problem as a Stackelberg game and then investigate the Stackelberg equilibrium for the proposed game. A Stackelberg game consists of two sets of players, namely, leaders and followers, where both of them try to maximize their revenues or profits. The leaders make a move first and then their followers will move according to the leaders' strategy. The leaders (private jammers) announce a set of unit interference prices for each eavesdropper. Then, the follower (transmitter) decides on the interference requirements at the eavesdroppers according to the interference prices.

## A. Stackelberg Game

The interference received at the  $l^{th}$  eavesdropper from the corresponding private jammer can be written as follows:

$$I_l = p_l |g_{jl}|^2, (6)$$

where  $|g_{jl}|^2$  is the power gain between the corresponding private jammer and the  $l^{\text{th}}$  eavesdropper and the power allocation at the  $l^{\text{th}}$  private jammer is represented by  $p_l$ . Here, we are only interested in the power allocation policy at the jammer, where the beamformer at the jammer is appropriately designed with no interference leakage to the legitimate users and hence interference is introduced only to the corresponding eavesdropper.

The private jammers' objective is to maximize their revenue by selling interference to the transmitter. The revenue of the  $l^{\text{th}}$ private jammer can be written as follows:

$$\phi_l(\mu_l, p_l) = \mu_l p_l |g_{jl}|^2, \tag{7}$$

where  $\mu_l$  is the unit interference price charged by the corresponding jammer to cause interference at the  $l^{\text{th}}$  eavesdropper. Depending on the interference requirement at the  $l^{\text{th}}$  eavesdropper, the interference price should be determined by the corresponding jammer to maximize its revenue. The prices for interference at each eavesdropper can be obtained by solving the following optimization problem:

Problem (A): 
$$\max_{\boldsymbol{\mu} \succeq \mathbf{0}} \sum_{l=1}^{L} \phi_l(\mu_l, p_l),$$
(8)

where  $\mu = [\mu_1 \cdots \mu_L]$  represents the interference prices for all the eavesdroppers.

At the same time, the transmitter should maximize its utility by introducing a price for secret communication established between the transmitter and the corresponding legitimate users. The revenue function at the transmitter can be written as

$$\psi_L(\mathbf{p}, \boldsymbol{\mu}) = \sum_{k=1}^K \lambda_k R_k - \sum_{l=1}^L \mu_l p_l |g_{jl}|^2,$$
(9)

<sup>&</sup>lt;sup>1</sup>Here, it is assumed that the jammers have the perfect CSI of the corresponding eavesdroppers. This is a reasonable assumption, for networks in which the eavesdroppers are also part of the system [16], [19], [23].

where  $\lambda_k$  and  $R_k$  are the unit price for the secrecy rate and the achievable secrecy rate at the  $k^{\text{th}}$  user, respectively. In addition, it is assumed that the unit price for the secrecy rate for each user is fixed at a certain value. Hence, the transmitter should determine the beamforming vector and decide on the interference requirements at different eavesdroppers to maximize its revenue. However, we are only interested in determining the interference requirements at each eavesdroppers for a given beamformer at the transmitter. This problem can be formulated as follows:

Problem (B): 
$$\max_{\mathbf{p} \succeq 0} \psi_L(\mathbf{p}, \boldsymbol{\mu}),$$
 (10)

where  $\mathbf{p} = [p_1 \cdots p_L]$  represents the power allocation policy at all jammers.

*Problem (A)* and *Problem (B)* form a Stackelberg game, in which the jammers (leaders) announce the interference prices at each eavesdropper and then the transmitter (follower) determines the required amount of interference to each eavesdropper. The solution of this game can be obtained by investigating the Stackelberg equilibrium, at which the transmitter and the jammers come to an agreement on the interference requirements and the interference price at each eavesdropper. The deviation of either the transmitter or the jammers from this equilibrium will introduce loss in their revenues.

## B. Stackelberg Equilibrium

The Stackelberg equilibrium for the proposed game is defined as follows:

Stackelberg equilibrium: Let  $\mathbf{p}^*$  be the optimal solution for *Problem (B)*, whereas  $\boldsymbol{\mu}^*$  contains the best prices for *Problem (A)*. The solutions  $\mathbf{p}^*$  and  $\boldsymbol{\mu}^*$  define a Stackelberg equilibrium point if the following conditions are satisfied for all  $\mathbf{p}$  and  $\boldsymbol{\mu}$ :

$$\psi_L(\mathbf{p}^*, \boldsymbol{\mu}^*) \ge \psi_L(\mathbf{p}, \boldsymbol{\mu}^*), \ \phi_l(p_l^*, \mu_l^*) \ge \phi_l(p_l^*, \mu_l), \forall \ l.$$

## V. STACKELBERG EQUILIBRIUM SOLUTION

In this section, we derive Stackelberg equilibrium solutions for the proposed game described in the previous section with different numbers of legitimate users and eavesdroppers. First, the best response of the transmitter is derived in terms of power allocation at the jammers for fixed interference prices. Then, the optimal interference prices are obtained to maximize the revenue of the jammers. In order to obtain the Stackelberg equilibrium points, the best responses of the follower (legitimate transmitter) and the leaders (jammers) should be obtained by solving Problem (B) and Problem (A), respectively. Since, the leaders (jammers) derive the optimal interference prices determined by the interference requirements from the legitimate transmitter, the best response function of the follower should be derived first in terms of the interference requirements. For the proposed game, the Stackelberg equilibrium can be derived by obtaining  $\mathbf{p}^*$  from *Problem (B)* first and then by obtaining the best interference prices  $\mu^*$  from *Problem* (*A*). In the following sections, we solve the proposed Stackelberg game with different numbers of legitimate users and eavesdroppers.

#### A. Single Legitimate User and Single Eavesdropper

In this section, the proposed game is considered with a single legitimate user and an eavesdropper. First, the optimal interference requirement (best response) at the transmitter is obtained to maximize its revenue for the fixed interference price at the jammer. Then, a Stackelberg equilibrium is derived for this game where both the legitimate transmitter and jammer attain an equilibrium by achieving their maximum revenues.

1) Fixed Interference Price: Here, the optimal interference requirement is obtained for a fixed interference price at the jammer. For a given beamformer at the transmitter, the achievable secrecy rate of the legitimate user in the presence of an eavesdropper is defined as

$$R_{SL-SE} = \log\left(1+\beta_0\right) - \log\left(1+\frac{\beta_1}{\sigma_e^2 + p_1\alpha_1}\right), \quad (11)$$

where

$$\beta_0 = \frac{\mathbf{w}^H \mathbf{h}_1 \mathbf{h}_1^H \mathbf{w}}{\sigma^2}, \ \beta_1 = \mathbf{w}^H \mathbf{g}_1 \mathbf{g}_1^H \mathbf{w}, \ \alpha_1 = |g_{j1}|^2.$$
(12)

Hence, the optimal interference requirement at the eavesdropper can be obtained by solving the following optimization problem:

$$\max_{p_1 \ge 0} \lambda_1 R_{SL-SE} - \mu_1 p_1 \alpha_1, \tag{13}$$

where  $p_1$  is the power allocation policy at the corresponding jammer. This problem is convex and the corresponding proof has been provided in the next section. Hence, the optimal power allocation can be obtained through standard interior point methods [44]. However, we derive the closed-form solution for the power allocation  $p_1$  to realize the Stackelberg equilibrium in the following section.

2) Stackelberg Game: In this section, we derive the Stackelberg equilibrium with a legitimate user and an eavesdropper. To obtain this equilibrium, the best response (i.e.,  $p_1^*$ ) of the follower (transmitter) is derived for a given interference price ( $\mu_1$ ), since the leader (jammer) derives its best response from the interference requirement decided by the follower (transmitter). Note that a closed-form solution for the best response should be obtained to derive the Stackelberg equilibrium of the proposed game. The best response of the follower can be obtained by solving the following problem:

$$\max_{p_1 \ge 0} \quad \psi_{\text{SL-SE}}(p_1, \mu_1), \tag{14}$$

$$\psi_{\text{SL-SE}}(p_1, \mu_1) = \lambda_1 \left[ \log \left( 1 + \frac{\mathbf{w}^H \mathbf{h}_1 \mathbf{h}_1^H \mathbf{w}}{\sigma_1^2} \right) - \log \left( 1 + \frac{\mathbf{w}^H \mathbf{g}_1 \mathbf{g}_1^H \mathbf{w}}{\sigma_e^2 + p_1 \alpha_1} \right) \right] - \mu_1 p_1 \alpha_1$$
(15)

in where  $\psi_{\text{SL-SE}}(p_1, \mu_1)$  is the revenue function for the transmitter and is defined in (15) at the top of the next page.  $\lambda_1$  and  $\mu_1$  are the unit prices for the secrecy rate at the legitimate user and the price for the interference introduced at the eavesdropper. The optimal interference requirement for a given w and  $\mu_1$  can

be obtained by solving the following problem:

$$\max_{p_1 \ge 0} \lambda_1 \left[ \log \left( 1 + \beta_0 \right) - \log \left( 1 + \frac{\beta_1}{\sigma_e^2 + p_1 \alpha_1} \right) \right] - \mu_1 p_1 \alpha_1,$$
(16)

where

$$\beta_0 = \frac{\mathbf{w}^H \mathbf{h}_1 \mathbf{h}_1^H \mathbf{w}}{\sigma_1^2}, \ \beta_1 = \mathbf{w}^H \mathbf{g}_1 \mathbf{g}_1^H \mathbf{w} \text{ and } \alpha_1 = |g_{j1}|^2.$$
(17)

*Lemma 2:* The optimal interference requirement from the jammer with a given interference price  $\mu_1$  is given by

$$p_1^* = \frac{1}{\alpha_1} \left[ \sqrt{\frac{\beta_1^2}{4} + \frac{\lambda_1 \beta_1}{\mu_1}} - \frac{(2\sigma_e^2 + \beta_1)}{2} \right]^+$$
(18)

*Proof:* Please refer to Appendix B.

*Corollary 1:* With a given w and  $\lambda_1$ , the interference price  $\mu_1$  is bounded as follows:

$$\mu_1 \le \frac{\lambda_1 \beta_1}{\sigma_e^2 \left(\sigma_e^2 + \beta_1\right)}.$$
(19)

Since  $p_1 \ge 0$ ,

$$\sqrt{\frac{\beta_1^2}{4} + \frac{\lambda_1 \beta_1}{\mu_1}} \geq \frac{(2\sigma_e^2 + \beta_1)}{2} \Rightarrow \mu_1 \leq \frac{\lambda_1 \beta_1}{\sigma_e^2 \left(\sigma_e^2 + \beta_1\right)}.$$
 (20)

We have thus obtained the optimal interference requirement at the eavesdropper to maximize the revenue of the legitimate transmitter. The jammer should announce the optimal unit interference price  $\mu_1$  to maximize its revenue by selling the interference to the transmitter. The optimal unit interference price can be obtained by solving the following optimization problem:

$$\max_{\mu_1 \ge 0} \phi_1(p_1^*, \mu_1) = \mu_1 p_1^* \alpha_1 \tag{21}$$

*Lemma 3:* The optimal unit interference price  $\mu_1$  is given as follows:

$$\mu_1^* = \frac{c_2}{2c_1} \left[ \frac{c_0}{\sqrt{c_0^2 - c_1}} - 1 \right],$$
(22)

where

$$c_0 = \frac{\left(2\sigma_e^2 + \beta_1\right)}{2\alpha_1}, \ \ c_1 = \frac{\beta_1^2}{4\alpha_1^2} \text{ and } c_2 = \frac{\lambda_1\beta_1}{\alpha_1^2}.$$
 (23)

Proof: Please refer to Appendix C.

Hence, a Stackelberg equilibrium for the proposed game with a single legitimate user and an eavesdropper is  $(p_1^*, \mu_1^*)$ . Any deviation from this equilibrium point will cause loss to both the follower (legitimate transmitter) and leader (jammer). Hence, both of them will operate at this Stackelberg equilibrium to maximize their revenues.

*Proposition 1:* There is a unique Nash equilibrium for the proposed game and the derived Stackelberg equilibrium solution achieves this unique Nash equilibrium.

*Proof:* As mentioned before, the revenue function of the legitimate transmitter is a concave function of the power allocation policy at the jammer. Hence, the optimal and unique jammer power allocation policy has been derived for a given

interference price. Similarly, the revenue function of the jammer is also a concave function in terms of the interference price which results in an optimal and unique interference price. Since, both solutions are unique and optimal, this equilibrium achieves a unique Nash equilibrium for the proposed game.

# B. Multiple Legitimate Users and Single Eavesdropper

In this section, we extend the proposed game to the scenario with multiple legitimate users and a single eavesdropper. As in the previous section, first, the optimal interference requirement is obtained for a fixed interference price and then, a Stackelberg equilibrium is derived for the proposed game.

1) Fixed Interference Price: The achievable secrecy rate of the  $i^{th}$  user can be defined as

$$R_{ML-SE}^{(i)} = \log\left(1+\beta_i\right) - \log\left(1+\frac{\beta_e}{\sigma_e^2+p_2\alpha_1}\right), \quad (24)$$

where

$$\beta_i = \frac{\mathbf{w}^H \mathbf{h}_i \mathbf{h}_i^H \mathbf{w}}{\sigma^2}, \quad \beta_e = \mathbf{w}^H \mathbf{g}_1 \mathbf{g}_1^H \mathbf{w} \quad \alpha_1 = |g_{j1}|^2.$$
(25)

The optimal power allocation policy at the jammer for a fixed interference price can be formulated as

$$\max_{p_1 \ge 0} \sum_{i=1}^{K} \lambda_i R_{SL-ME}^{(i)} - \mu_1 p_2 \alpha_1.$$
 (26)

*Lemma 4:* The optimal power allocation policy at the jammer to maximize the revenue at the legitimate transmitter is given by

$$p_{2}^{*} = \frac{1}{\alpha_{1}} \left[ \sqrt{\frac{\beta_{e}^{2}}{4} + \frac{\beta_{e} \left( \sum_{i=1}^{K} \lambda_{i} \right)}{\mu_{1}}} - \frac{\left( 2\sigma_{e}^{2} + \beta_{e} \right)}{2} \right]^{+}.$$
 (27)

*Proof:* The proof is similar to that of Lemma 2.

2) *Stackelberg Game:* In order to derive the Stackelberg equilibrium with multiple legitimate users and an eavesdropper, the best response of jammer should be obtained by solving the following problem:

$$\max_{\mu_2 \ge 0} \phi_1(p_2^*, \mu_2) = \mu_2 p_2^* \alpha_1.$$
(28)

*Lemma 5:* The optimal unit interference price  $\mu_2$  is given as follows:

$$\mu_2^* = \frac{\bar{c}_2}{2c_1} \left[ \frac{c_0}{\sqrt{c_0^2 - c_1}} - 1 \right],$$
(29)

where

$$c_0 = \frac{\left(2\sigma_e^2 + \beta_e\right)}{2\alpha_1}, \ c_1 = \frac{\beta_e^2}{4\alpha_1^2} \text{ and } \bar{c}_2 = \frac{\beta_e \sum_{i=1}^K \lambda_i}{\alpha_1^2}.$$
 (30)

*Proof:* The proof is similar to that of Lemma 3.

Hence, the Stackelberg equilibrium of the proposed game with multiple legitimate users and a single eavesdropper is given by  $(p_2^*, \mu_2^*)$ .

## C. Single Legitimate User and Multiple Eavesdroppers

Here, the proposed game is investigated with a single legitimate user and multiple eavesdroppers. This problem is different from the above problems due to the fact that there are multiple active eavesdroppers. As in the previous section, first the fixedinterference scenario is solved, followed by the derivation of the Stackelberg equilibrium of the proposed game.

1) Fixed Interference Prices: The achievable secrecy rate with multiple eavesdroppers can be defined as

$$R_{SL-ME} = \log\left(1+\beta_0\right) - \max_{1 \le i \le L} \log\left(1+\frac{\beta_i}{\sigma_e^2 + p_i \alpha_i}\right),\tag{31}$$

where

$$\beta_0 = \frac{\mathbf{w}^H \mathbf{h}_1 \mathbf{h}_1^H \mathbf{w}}{\sigma^2}, \ \beta_i = \mathbf{w}^H \mathbf{g}_i \mathbf{g}_i^H \mathbf{w}, \ \alpha_i = |g_{ji}|^2.$$
(32)

Note that all the eavesdroppers may not necessarily influence the achievable secrecy rate at the legitimate user. The eavesdropper with the highest achieved rate will determine the achieved secrecy rate of the legitimate user. By introducing jamming to this eavesdropper, the secrecy rate can be improved by reducing the achievable rate at the corresponding eavesdropper. After this jamming, another eavesdropper might now have the highest achievable rate which will deteriorate the achievable secrecy rate of the legitimate user. Hence, it is important to jam this eavesdropper in order to match the achieved rate of the previous eavesdropper. Therefore, only a subset of eavesdroppers require the interference from the jammers and the rest of them do not need any interference from the jammers, since their impact on the secrecy rate is not dominant. Here, we divide these eavesdroppers into two sets, namely, super-active and non-super-active eavesdroppers. The eavesdroppers who receive interference from the jammers and determine the achievable secrecy rate of the legitimate user are called super-active eavesdroppers and the rest of them are defined as non-super-active eavesdroppers. In order to improve the revenue of the legitimate transmitter, the optimal interference requirements problem can be formulated as follows:

$$\max_{\mathbf{p} \succeq \mathbf{0}} \lambda_1 R_{SL-ME} - \sum_{i \in \mathbb{K}} \mu_i p_i \alpha_i, \tag{33}$$

where the vector  $\mathbf{p} = \{p_i \mid i \in \mathbb{K}\}\$  represents the power allocations of private jammers in the set  $\mathbb{K}$  consisting of all superactive eavesdroppers. The optimal interference requirements from private jammers corresponding to the super-active eavesdroppers can be obtained by formulating the problem as follows:

$$\max_{\mathbf{p} \succeq \mathbf{0}, t_i, t_0} \quad \lambda_1 \left[ \log \left( 1 + \beta_0 \right) - t_0 \right] - \sum_{i \in \mathbb{K}} \mu_i p_i \alpha_i$$
  
s.t. 
$$\log \left( 1 + \frac{\beta_i}{\sigma_e^2 + p_i \alpha_i} \right) \le t_i, \ i \in \mathbb{K}$$
$$\max\{t_i \setminus i \in \mathbb{K}\} = t_0, \ t_i \ge 0, \ i \in \mathbb{K}.$$
(34)

The problem in (34) is convex in p and can be easily solved by interior point methods. However, one issue that might arise is how to obtain the super-active eavesdroppers' set  $\mathbb{K}$  from all available active eavesdroppers. This can be addressed by solving the following optimization problem:

$$\max_{\mathbf{p} \succeq \mathbf{0}, t_i, t_0} \lambda_1 \left[ \log \left( 1 + \beta_0 \right) - t_0 \right] - \sum_{i=1}^L \mu_i p_i \alpha_i$$
  
s.t. 
$$\log \left( 1 + \frac{\beta_i}{\sigma_e^2 + p_i \alpha_i} \right) \le t_i, \forall i$$
$$\max\{t_1, \cdots, t_L\} = t_0, \ t_i \ge 0, \forall i, \quad (35)$$

where the super-active eavesdroppers' set  $\mathbb{K}$  is removed and all the available eavesdroppers have been incorporated into the optimization problem.

Proposition 2: : At the optimal solution of (35), the achieved rates of the super-active eavesdroppers (i.e.,  $t_i$ ,  $i \in \mathbb{K}$ ) will be equal and the power allocations  $p_i$  of non-super-active eavesdroppers (i.e.,  $i \notin \mathbb{K}$ ) will be all zeros.

*Proof:* Assume that  $t_i$ ,  $i \in \mathbb{K}$ , are not equal. Let us consider the minimum  $t_i = t_{\min} < t_0$  from all  $t_i$ ,  $i = 1, \dots, L$ , and the corresponding  $p_i$  will be higher than that of  $t_{\min} = t_0$ . Hence, the revenue of the transmitter (cost function of (35)) with  $t_i$  $= t_{\min}$  will be less than that with  $t_i = t_0$ . Thus, the achieved rates of the super-active eavesdroppers (i.e.,  $t_i$ ,  $i \in \mathbb{K}$ ) will be equal at the optimal solution and the power allocations strategy corresponding to the non-super-active eavesdroppers (i.e.,  $i \notin \mathbb{K}$ ) will be zeros.

Therefore, the optimal interference requirements from the private jammers with fixed interference prices can be obtained by solving the convex problem in (35).

2) *Stackelberg Game:* As in the previous sections, this problem is formulated as a Stackelberg game and the Stackelberg equilibrium is defined for the proposed game. The best response of the transmitter for a given set of interference prices can be determined by solving the following problem:

$$\max_{\mathbf{p} \succeq \mathbf{0}} \lambda_1 R_{SL-ME} - \sum_{i \in \mathbb{K}} \mu_i p_i \alpha_i, \tag{36}$$

where **p** represents power allocations of the private jammers in the set  $\mathbb{K}$  which is the set consisting of all the super-active eavesdroppers. This problem can be formulated into a convex problem as in (35) and the optimal power allocation strategy can be obtained. However, it is necessary to find a closed-form solution to derive a Stackelberg equilibrium for the proposed game.

*Lemma 6:* The optimal power allocation policy at the  $i^{th}$  jammer is given by

$$p_i^* = \frac{1}{\alpha_i} \left[ \frac{\beta_i}{\gamma_0^*} - \sigma_e^2 \right]^+, \qquad (37)$$

where

$$\beta_{i} = \mathbf{w}^{H} \mathbf{g}_{i} \mathbf{g}_{i}^{H} \mathbf{w}$$
$$\gamma_{0}^{*} = \frac{\sum_{i=1}^{K} \mu_{i} \beta_{i} + \sqrt{\sum_{i=1}^{K} \mu_{i} \beta_{i} \left(4\lambda_{1} + \sum_{i=1}^{K} \mu_{i} \beta_{i}\right)}{2\lambda_{1}}.$$
 (38)

*Proof:* Please refer to Appendix D.

The optimal interference requirement has been derived to maximize the transmitter's revenue for a given set of interference prices. However, the jammers should announce their optimal interference prices to maximize their revenues. The optimal interference price can be obtained by solving the following problem:

$$\max_{\boldsymbol{\mu} \succeq \mathbf{0}} \sum_{l=1}^{L} \phi_i(p_i^*, \mu_i) = \sum_{l=1}^{L} \mu_i p_i^* \alpha_i.$$
(39)

By substituting the optimal power allocations  $p_i^*$  in (37) in terms of the interference prices  $\mu_i$ , the above optimization problem can be rewritten as

$$\max_{\boldsymbol{\mu} \succeq \mathbf{0}} \left[ \frac{2\lambda_1 \sum_{i=1}^{K} \mu_i \beta_i}{\sum_{i=1}^{K} \mu_i \beta_i + \sqrt{\sum_{i=1}^{K} \mu_i \beta_i} \left( 4\lambda_1 + \sum_{i=1}^{K} \mu_i \beta_i \right)} - \sigma_e^2 \sum_{i=1}^{K} \mu_i \right]^+.$$
(40)

It is very difficult to find a closed-form solution for the optimal interference prices  $\mu_i$  and the problem in (40) generally must be solved using existing numerical methods. However, we can find a closed-form solution if we assume that each private jammer announces the same interference prices (i.e.,  $\mu_1 = \mu_2 = \cdots = \mu_L = \mu_0$ ). For this uniform interference price scenario, the optimization problem in (40) can be modified as

$$\max_{\mu_{0} \geq 0} \left[ \frac{2\lambda_{1}\mu_{0}\sum_{i=1}^{K}\beta_{i}}{\mu_{0}\sum_{i=1}^{K}\beta_{i} + \sqrt{\mu_{0}\sum_{i=1}^{K}\beta_{i}\left(4\lambda_{1} + \mu_{0}\sum_{i=1}^{K}\beta_{i}\right)}} - K\sigma_{e}^{2}\mu_{0} \right]^{+}.$$
(41)

*Lemma 7:* The optimal interference price  $\mu_0^*$  in (41) is given by

$$\mu_0^* = \frac{\frac{1}{2} \left[ -4\lambda_1 K \sigma^2 \eta_1 + 2\lambda_1 \sqrt{K \sigma^2 \eta_2 + 4K^2 \sigma^4 \eta_1^2} \right]}{K \sigma^2 \eta_2} \quad (42)$$

where

$$\eta_1 = \left(1 + \frac{K\sigma^2}{\bar{c}_2}\right), \ \eta_2 = \left(\bar{c}_2 + K\sigma^2\right), \ \bar{c}_2 = \sum_{i=1}^K \beta_i.$$
(43)

Proof: Please refer to Appendix E.

The Stackelberg equilibrium of the proposed uniform price game with a single legitimate user and multiple eavesdroppers is given by  $(p_i^* \forall i, \mu_0^*)$ . By using this equilibrium solution, both the legitimate transmitter and the jammers achieve their maximum revenues.

# D. Multiple Legitimate Users and Multiple Eavesdroppers

In this section, the proposed game is extended to the scenario with multiple legitimate users and multiple eavesdroppers. As in the previous sections, the fixed interference price scenario and Stackelberg game are investigated. 1) Fixed Interference Prices: The achievable secrecy rate of the  $i^{th}$  user can be defined as

$$R_{ML-ME}^{(i)} = \log\left(1+\beta_0^{(i)}\right) - \max_{1 \le i \le L} \log\left(1+\frac{\beta_i}{\sigma_e^2 + p_i\alpha_i}\right),\tag{44}$$

where

$$\beta_0^{(i)} = \frac{\mathbf{w}^H \mathbf{h}_i \mathbf{h}_i^H \mathbf{w}}{\sigma^2}, \quad \beta_i = \mathbf{w}^H \mathbf{g}_i \mathbf{g}_i^H \mathbf{w}.$$
(45)

As mentioned in the previous section, all the eavesdroppers might not be active due to the different achieved rates. By considering only super-active eavesdroppers, the optimal interference requirements can be obtained by solving the following problem:

$$\max_{\mathbf{p} \succeq \mathbf{0}} \sum_{i=1}^{K} \lambda_i R_{SL-ME}^{(i)} - \sum_{i \in \mathbb{K}} \mu_i p_i \alpha_i, \qquad (46)$$

where the vector  $\mathbf{p}$  represents power allocations of private jammers in the set  $\mathbb{K}$  which is the set consisting of all the active eavesdroppers. As in the previous section, the optimal interference requirements can be obtained by considering both super-active and non-super-active eavesdroppers through the following problem:

$$\max_{\mathbf{p} \succeq \mathbf{0}, t_i, t_0} \sum_{i=1}^{K} \lambda_i \left[ \log \left( 1 + \beta_0^{(i)} \right) - t_0 \right] - \sum_{i=1}^{L} \mu_i p_i \alpha_i$$
  
s.t. 
$$\log \left( 1 + \frac{\beta_i}{\sigma_e^2 + p_i \alpha_i} \right) \le t_i, \forall i$$
$$\max\{t_1, \cdots, t_L\} = t_0, \forall i, t_i \ge 0, \forall i.$$
(47)

At the optimal solution of (47), the achieved rates of the super-active eavesdroppers will be equal and power allocations corresponding to the non-super-active eavesdroppers will be zeros, where the corresponding proof is similar to that of Proposition 2.

2) Stackelberg Game: Here, we solve the Stackelberg game for the scenario with multiple legitimate users and multiple eavesdroppers. The derivation of the Stackelberg equilibrium is similar to that of the scenario with a single legitimate user and multiple eavesdroppers. The best response of the legitimate transmitter can be obtained by solving the following problem:

$$\max_{\mathbf{p} \succeq \mathbf{0}} \sum_{i=1}^{K} \lambda_i R_{ML-ME}^{(i)} - \sum_{i \in \mathbb{K}} \mu_i p_i \alpha_i, \qquad (48)$$

where the vector **p** consists of all the power allocations of the jammers corresponding to the super-active eavesdroppers.

*Lemma 8:* The optimal power allocation strategy at the  $i^{\text{th}}$  jammer is given by

$$p_{i_{ML-ME}}^* = \frac{1}{\alpha_i} \left[ \frac{\beta_i}{\gamma_1} - \sigma_e^2 \right]^+, \qquad (49)$$

where

$$\beta_{i} = \mathbf{w}^{H} \mathbf{g}_{i} \mathbf{g}_{i}^{H} \mathbf{w}$$
$$\gamma_{1} = \frac{\sum_{i=1}^{K} \mu_{i} \beta_{i} + \sqrt{\sum_{i=1}^{K} \mu_{i} \beta_{i} \left(4 \sum_{i=1}^{K} \lambda_{i} + \sum_{i=1}^{K} \mu_{i} \beta_{i}\right)}{2 \sum_{i=1}^{K} \lambda_{i}}$$



For this interference requirement, the jammers should determine their optimal interference prices to maximize their revenues which can be obtained by solving the following problem:

$$\max_{\boldsymbol{\mu} \succeq \mathbf{0}} \sum_{i=1}^{K} \phi_i(p_i^*, \mu_i) = \sum_{i=1}^{L} \mu_i p_i^* \alpha_i.$$
 (50)

However, it is difficult to find a closed-form optimal solution for the problem in (50) with different interference prices  $\mu_i$  at each jammer. In the case of the uniform interference price (i.e.,  $\mu_1 = \mu_2 = \cdots, \mu_L = \mu_0$ ), the problem in (50) can be modified as follows:

$$\max_{\mu_0 \ge 0} \frac{2\mu_0 \bar{c}_3 \bar{c}_2}{\mu_0 \bar{c}_2 + \sqrt{\mu_0 \bar{c}_2 \left(4\bar{c}_3 + \mu_0 \bar{c}_2\right)}} - K \sigma_e^2 \mu_0 \qquad (51)$$

where

$$\bar{c}_2 = \sum_{i=1}^{K} \beta_i, \ \bar{c}_3 = \sum_{i=1}^{K} \lambda_i.$$
 (52)

*Lemma 9:* The optimal interference price  $\mu_0^*$  is given by

$$\mu_{ML-ME}^{*} = \frac{\frac{1}{2} \left[ -4K\sigma^{2}\bar{c}_{3}\eta_{1} + 2\bar{c}_{3}\sqrt{K\sigma^{2}\eta_{2} + 4K^{2}\sigma^{4}\eta_{1}^{2}} \right]}{K\sigma^{2}\eta_{2}}$$
(53)

where

$$\eta_1 = 1 + \frac{K\sigma^2}{\bar{c}_2}, \ \eta_2 = \bar{c}_2 + K\sigma^2.$$
 (54)

*Proof:* The proof is similar to that of Lemma 7.

Hence, a Stackelberg equilibrium of the proposed game with multiple legitimate users and multiple users is defined by  $(p_{i_{ML-ME}}^*, \forall i, \mu_{ML-ME}^*)$  which provides the maximum revenues for both the legitimate transmitter and the private jammers.

#### VI. SIMULATION RESULTS

In this section, we provide simulation results to support the theoretical results derived in the previous sections. In order to evaluate the performance of the proposed schemes, we consider a multicasting secrecy network in which the transmitter broadcasts the same information to all the legitimate users in the presence of multiple eavesdroppers. In addition, private jammers are employed to confuse the eavesdroppers by introducing interference in order to improve the secrecy rates at the legitimate users. The legitimate transmitter is equipped with three antennas, whereas each of the legitimate users and eavesdroppers has a single-antenna. The unit secrecy rate price has been set to 5 (i.e.,  $\lambda_1 = 5$ ). In this secrecy network, all channels have been generated using zero-mean circularly symmetric independent and identically distributed complex Gaussian random variables. The noise power at all the terminals has been assumed to be 0.1.

TABLE I THE REQUIRED TRANSMIT POWER FOR THE CLOSED-FORM AND CONVEX OPTIMIZATION BASED SOLUTIONS

Channels	Required Transmit Power				
	Closed Form	Convex Optimization			
Channel 1	1.1610	1.1610			
Channel 2	1.3431	1.3431			
Channel 3	1.2069	1.2069			
Channel 4	0.7455	0.7455			
Channel 5	0.6082	0.6082			



Fig. 3. The revenue of the legitimate transmitter versus the power allocation at the private jammer for different channels with a fixed interference price (i.e.,  $\mu_1 = 1$ ).

#### A. Power Minimization

In this section, we provide simulation results to support the closed-form results derived in (3) for the scenario with a single legitimate user and an eavesdropper. As mentioned before, the original power minimization problem can be formulated into a convex optimization (SOCP) framework. However, we derived a closed-form solution in (3). We have obtained the required transmit power and the corresponding beamformer based on the closed-form solution as well as the convex optimization framework for different sets of channels as provided in Table I where the target secrecy rate has been set to 3.5. As seen in Table I, both results are the same which validates the accuracy of the closed-form solution in (3). Due to space limitations, the performance for the corresponding beamformers and the simulation results for the case with multiple legitimate users and multiple eavesdroppers are not provided here.

## **B.** Fixed Interference Prices

In this section, we evaluate the performance of the proposed schemes with private jammers, where the legitimate transmitter is charged with fixed interference prices. The simulation results are provided with different numbers of legitimate users and eavesdroppers.

1) Single Legitimate User and Single Eavesdropper: A secrecy network with a single legitimate user and an eavesdropper

Channels	Power Allocation: Jammer		Achieved S	Secrecy Rate	Revenue: Legitimate Transmitt	
	Derivation	Simulation	Derivation	Simulation	Derivation	Simulation
Channel 1	1.1809	1.2000	1.6445	1.6458	7.8207	7.8206
Channel 2	1.5019	1.5000	2.0534	2.0531	8.9325	8.9325
Channel 3	3.5984	3.6000	2.0505	2.0507	7.4198	7.4198
Channel 4	0.9452	1.0000	1.9921	2.0041	8.6606	8.6583
Channel 5	2.4107	2.4000	1.8168	1.8152	7.2427	7.2427

TABLE IITHE OPTIMAL POWER ALLOCATION POLICY OF THE PRIVATE JAMMERS WITH FIXED INTERFERENCE PRICES  $\mu_1 = 1$ , ACHIEVABLE SECRECY RATES ANDREVENUES OF THE LEGITIMATE TRANSMITTER FOR A SINGLE LEGITIMATE TRANSMITTER AND SINGLE EAVESDROPPER OBTAINED FROM THE CLOSED-FORM<br/>SOLUTION AND SIMULATION FOR DIFFERENT SETS OF CHANNELS

is considered in which a private jammer introduces interference to the eavesdropper by charging the legitimate transmitter a price of one (i.e.,  $\mu_1 = 1$ ) for unit interference. First, we validate the concavity of the revenue function of the legitimate transmitter  $(f(p_1) \text{ in } (60))$  in terms of the power allocation  $(p_1)$  at the private jammer and then simulation results based optimal power allocations are obtained to support the theoretical derivations. Fig. 3 shows the revenue function of the legitimate transmitter for different sets of channels for a fixed interference price. As seen in Fig. 3, the revenue functions are concave for different sets of channels, which validates the proof of the convexity of  $f(p_1)$  provided in Appendix B. On the other hand, Table II presents the optimal power allocation policy at the private jammer, the achieved secrecy rate and the corresponding revenue of the legitimate transmitter obtained through theoretical and simulation results. As seen in Table II, the theoretical and simulation results are identical, which demonstrates the accuracy of the derivations in (18). In addition, the optimal power allocations at the jammer corresponding to the maximum revenue at transmitter in Fig. 3 is the same as the theoretical results in Table II for the five channels considered in this simulation. Hence, these results confirm the optimality of the derived results for the scenario of the single legitimate user and the single eavesdropper.

2) Single Legitimate User and Multiple Eavesdroppers: Here, we consider a multicasting secrecy network with a single legitimate user and two eavesdroppers. The price used by the jammers to charge the legitimate transmitter is 1 and 3 (i.e.,  $\mu_1 = 1, \ \mu_2 = 3$ ), respectively, for unit interference. Similar to the previous simulations, first, we validate the convexity of the revenue function of the legitimate transmitter in (35) in terms of power allocations (i.e.,  $p_1$  and  $p_2$ ) at the private jammers for different sets of channels. Then, the correctness of the derived theoretical results is supported through numerical results. Fig. 4 depicts the revenue functions of the legitimate transmitter for Channel 1 provided in Table III which confirms the convexity of the revenue function in terms of power allocation policy at the jammers. In addition, Table III provides the theoretical and simulation based optimal power allocations at the private jammers which maximize the revenue of the transmitter for five sets of channels. As seen in Table III, the theoretical and simulation results are indistinguishable, which validates the derivation of the closed-form power allocations in (37). On the other hand, the maximum revenue from Fig. 4 is the same as that of



Fig. 4. The revenue of the legitimate transmitter for Channel 1 with different power allocations at the private jammers for fixed interference prices.

Channel 1 in Table III with the same power allocations at the private jammers. This confirms the optimality of the results obtained in Table III for different sets of channels. Note that we have only presented the revenue of the transmitter for Channel 1 in Fig. 4; however, the rest of the channels in Table III provide similar results. We have not presented those results here due to space limitations.

# C. Stackelberg Game

In this section, we validate the equilibrium of the proposed Stackelberg games for different numbers of legitimate users and eavesdroppers.

1) Single Legitimate User and Single Eavesdropper: To support the derived Stackelberg equilibrium, a secrecy network with a single legitimate user and an eavesdropper is considered. First, for different sets of channels, the revenue function of the jammer is evaluated with different interference prices as shown in Fig. 5. These results confirm that the jammer revenue function is concave with respect to the interference price (i.e.,  $\mu_1$ ) and support the proof provided in Appendix C. The choices for the optimal interference prices and the maximum revenues of the jammers are provided in Table IV, which verifies the accuracy of the analytical results. The Stackelberg equilibria ( $p_1^*, \mu_1^*$ ) for

TABLE IIITHE OPTIMAL POWER ALLOCATION POLICY OF THE PRIVATE JAMMERS WITH FIXED INTERFERENCE PRICES  $\mu_1 = 1$  and  $\mu_2 = 3$ ,ACHIEVABLE SECRECY RATES AND REVENUES OF THE LEGITIMATE TRANSMITTER

Channels	Power Allocation: Jammer 1		Power Allocation: Jammer 2		Achieved Secrecy Rate		Revenue: Legitimate Transmitter	
	Derivation	Simulation	Derivation	Simulation	Derivation	Simulation	Derivation	Simulation
Channel 1	0.3324	0.3324	0.7457	0.7458	2.7083	2.7241	13.0855	12.8145
Channel 2	0.1264	0.1264	0.5729	0.5430	3.3334	3.3223	15.2002	15.2016
Channel 3	3.3886	3.3889	1.0284	1.0284	2.8085	2.8234	13.4161	13.4203
Channel 4	1.1613	1.1614	1.0441	1.0442	2.9185	2.9296	13.7907	13.7928
Channel 5	0.2778	0.2778	2.0209	2.0211	3.2938	3.2949	15.1031	15.1031

The unit price for the achieved secrecy rate at the legitimate user is 5 ( $\lambda_1 = 5$ ).



Fig. 5. The revenue of the jammer with a single legitimate user and a single eavesdropper for different sets of channels.

TABLE IV THE OPTIMAL INTERFERENCE PRICES AND REVENUES OF THE PRIVATE JAMMER AND THE STACKELBERG EQUILIBRIUM FOR DIFFERENT SETS OF CHANNELS

Channels	Interference Price ( $\mu_1$ ):		Revenue of	Jammer:	Stackelberg Equilibrium: $(p_1^*, \mu_1^*)$	
	Derivation	Simulation	Derivation	Simulation	•	
Channel 1	4.4313	4.4000	0.5534	0.5530	(0.3670, 4.4313)	
Channel 2	8.5462	8.5000	2.2242	2.2240	(0.2929, 8.5462)	
Channel 3	5.6251	5.6000	3.6714	3.6715	(0.8291, 5.6251)	
Channel 4	8.5640	8.6000	2.1736	2.1735	(0.1863, 8.5640)	
Channel 5	7.8066	7.8000	2.8496	2.8495	(0.4779, 7.8066)	

The unit price for the achieved secrecy rate at the legitimate user is 5 ( $\lambda_1 = 5$ ).

the proposed game are also presented in Table IV. These validate the derived unique Stackelberg equilibrium of the game through simulation results, where both the transmitter and the private jammer will come to an agreement to maximize their revenues.

2) Single Legitimate User and Multiple Eavesdroppers: In order to validate the proposed Stackelberg equilibrium, the same



Fig. 6. The revenue of the transmitter versus  $\gamma_0$  with fixed interference prices for different sets of channels.

secrecy network as in the fixed interference price case is considered with a single legitimate user and multiple eavesdroppers. First, we evaluate the revenue function of the legitimate transmitter  $(f(\gamma_0))$  in (76) versus  $\gamma_0$  for different sets of channels. Fig. 6 plots the revenues of the legitimate transmitter versus  $\gamma_0$ with fixed interference prices (i.e.,  $\mu_1 = 1$ ,  $\mu_2 = 3$ ) for different sets of channels. This confirms the derivation of the convexity of  $f(\gamma_0)$  (Appendix D) as a function of  $\gamma_0$ . In addition, the achievable maximum revenues are the same as the derived solutions represented in Table V. Next, we evaluate the achievable revenues of the jammers with different interference prices where it is assumed that all the jammers introduce the same interference price (i.e.,  $\mu_1 = \mu_2 = \mu_0$ ). Fig. 7 plots the revenues of the jammers versus the interference price  $\mu_0$  for different sets of channels which confirms the convexity of the revenue of the jammers in the interference price  $\mu_0$  (Appendix E). Table V provides the theoretical and simulation based optimal interference prices (i.e.,  $\mu_0^*$  s) and corresponding revenues of the jammers for the proposed Stackelberg game with different sets of channels, where the theoretical results are the same as the simulated results. In addition, Stackelberg equilibria of the proposed game are also provided in Table V. The deviation of the legitimate transmitter and jammers from this equilibrium solution will

TABLE V THE OPTIMAL INTERFERENCE PRICES AND REVENUES OF THE PRIVATE JAMMERS AND THE STACKELBERG EQUILIBRIUM FOR DIFFERENT SETS OF CHANNELS

Channels	Interference Price:		Revenue o	f Jammers:	Stackelberg Equilibrium: $(p_1^*, p_2^*, \mu$
	Derivation	Simulation	Derivation	Simulation	
Channel 1	4.0721	4.1000	1.5381	1.5378	(0.0677, 0.3070, 4.0721)
Channel 2	2.1647	2.2000	0.5372	0.5378	(0.3076, 0.6900, 2.1647)
Channel 3	2.6639	2.7000	0.7088	0.7084	(0.1501, 1.0917, 2.6639)
Channel 4	3.1023	3.1000	0.8887	0.8892	(0.1501, 0.6996, 3.1023)
Channel 5	4.0322	4.0000	1.4932	1.4935	(2.5895, 0.7858, 4.0322)

The unit price for the achieved secrecy rate at the legitimate user is 5 ( $\lambda_1 = 5$ ).



Fig. 7. The revenue of the jammer versus the interference price for different sets of channels.

introduce a loss in their corresponding revenues as evidenced by Figs. 6 and 7.

## VII. CONCLUSION

In this paper, we have proposed optimization techniques for a multicasting secrecy network. For the scenario with a single legitimate user and a single eavesdropper, a closedform solution has been derived for the power minimization problem based on the corresponding dual problem, whereas it was formulated as a semidefinite programming problem in the case with multiple legitimate users and multiple eavesdroppers. On the other hand, optimization problems have been considered for a multicasting secrecy network with jammers to improve the achievable secrecy rates. These private jammers introduce charges for their jamming services. For fixed interference prices, we have derived the optimal interference requirements for different numbers of legitimate users and eavesdroppers. For non-fixed interference prices, we have formulated the optimization problem into a Stackelberg game in which jammers and the transmitter are the leaders and follower, respectively. A Stackelberg equilibrium has been developed for the proposed game with different numbers of legitimate users and eavesdroppers. To validate the derived theoretical

results, simulation results have been provided for a variety of scenarios.

## APPENDIX A

## Proof of Lemma 1

The original power minimization problem in (2) can be written without of loss of generality as

$$\min_{p, \tilde{\mathbf{w}}} p \tilde{\mathbf{w}}^{H} \tilde{\mathbf{w}}$$
s.t. 
$$\frac{\tilde{\mathbf{w}}^{H} \left( \mathbf{I} + p \hat{\mathbf{h}}_{1} \hat{\mathbf{h}}_{1}^{H} \right) \tilde{\mathbf{w}}}{\tilde{\mathbf{w}}^{H} \left( \mathbf{I} + p \hat{\mathbf{g}}_{1} \hat{\mathbf{g}}_{1}^{H} \right) \tilde{\mathbf{w}}} \geq 2^{\bar{R}_{s}}, \ \tilde{\mathbf{w}}^{H} \tilde{\mathbf{w}} = 1, \ p \geq 0, \ (55)$$

where  $\hat{\mathbf{h}}_1 = \frac{\mathbf{h}_1}{\sigma_1}$  and  $\hat{\mathbf{g}}_1 = \frac{\mathbf{g}_1}{\sigma_e}$ . In order to obtain the optimal solution of (55) (i.e.,  $\tilde{\mathbf{w}}^*, p^*$ ), we derive the corresponding dual problem. The Lagrangian of (2) can be defined as

$$\begin{split} L\left(\mathbf{w}, \lambda_{s}\right) &= \mathbf{w}^{H} \mathbf{w} + \lambda_{s} \left[2^{\bar{R}_{s}} \left(1 + \mathbf{w}^{H} \hat{\mathbf{g}}_{1} \hat{\mathbf{g}}_{1}^{H} \mathbf{w}\right) \right. \\ &- \left. \left(1 + \mathbf{w}^{H} \hat{\mathbf{h}}_{1} \hat{\mathbf{h}}_{1}^{H} \mathbf{w}\right) \right], \end{split}$$

where  $\lambda_s$  is the Lagrange multiplier associated with the secrecy rate constraint. The corresponding dual problem can be defined as

$$\max_{\lambda_s \ge 0} \lambda_s \left( 2^{R_s} - 1 \right), \text{ s.t. } \mathbf{Z} \triangleq \mathbf{I} - \lambda_s \left( \mathbf{\hat{h}} \mathbf{\hat{h}}^H - 2^{\bar{R}_s} \mathbf{\hat{g}}_1^H \mathbf{\hat{g}}_1 \right) \succeq \mathbf{0}.$$
(56)

The constraint in (56) means that the matrix  $\mathbf{Z}$  should have at least one zero eigenvalue. On the other hand,  $\lambda_s$  can take the maximum to satisfy the positive semidefinite constraint in (56) as

$$\lambda_s^* = \frac{1}{\lambda_{\max}\left(\hat{\mathbf{h}}\hat{\mathbf{h}}^H - 2^{\bar{R}_s}\hat{\mathbf{g}}_1^H\hat{\mathbf{g}}_1\right)},\tag{57}$$

where  $\lambda_{\max}(\cdot)$  denotes the maximum eigenvalue of its argument. The original problem in (2) can be formulated as a convex problem. Hence, strong duality holds between the original problem in (2) and the corresponding dual problem in (56). The required minimum power to achieve the secrecy rate constraint is

$$p^* = \lambda_s^* \left( 2^{\bar{R}_s} - 1 \right).$$
 (58)

On the other hand, the optimal w should be in the null space of Z:

$$\mathbf{w}_1 = v_{\max} \left( \hat{\mathbf{h}} \hat{\mathbf{h}}^H - 2^{R_s} \hat{\mathbf{g}}_1^H \hat{\mathbf{g}}_1 \right), \ \tilde{\mathbf{w}}^* = \frac{\mathbf{w}_1}{\|\mathbf{w}_1\|_2}, \qquad (59)$$

where  $v_{\max}(\cdot)$  denotes the the eigenvector corresponding to the maximum eigenvalue. Hence the optimal solution of (2) can be expressed as in (3). This completes the proof of Lemma 1.

## APPENDIX B

## Proof of Lemma 2

We first show that the problem in (16) is a convex problem by showing that the following function is concave in  $p_1$ :

$$f(p_1) = \lambda_1 \left[ \log (1 + \beta_0) - \log \left( 1 + \frac{\beta_1}{\sigma_e^2 + p_1 \alpha_1} \right) \right] - \mu_1 p_1 \alpha_1.$$
(60)

The concavity of this function can be shown by finding the second derivative respect to  $p_1$  as follows:

$$\frac{\partial f(p_1)}{\partial p_1} = \frac{\lambda_1 \alpha_1 \beta_1}{(\sigma_e^2 + p_1 \alpha_1 + \beta_1)(\sigma_e^2 + p_1 \alpha_1)} - \mu_1 \alpha_1 \quad (61)$$

$$\frac{\partial^2 f(p_1)}{\partial p_1^2} = -\frac{\lambda_1 \alpha_1 \beta_1 \left(2\alpha_1^2 p_1 + 2\alpha_1 \sigma_e^2 + \beta_1 \alpha_1\right)}{\left[\alpha_1^2 p_1^2 + \left(2\sigma_e^2 + \beta_1\right) \alpha_1 p_1 + \beta_1 \sigma_e^2 + \sigma_e^4\right]^2}.$$
(62)

Since  $\frac{\partial^2 f(p_1)}{\partial p_1^2} < 0$ ,  $f(p_1)$  is a concave function in terms of  $p_1$ . Hence the optimal solution should satisfy the KKT conditions as follows [44]:

$$\frac{\partial f(p_1)}{\partial p_1} = \frac{\lambda_1 \alpha_1 \beta_1}{(\sigma_e^2 + p_1 \alpha_1 + \beta_1)(\sigma_e^2 + p_1 \alpha_1)} - \mu_1 \alpha_1 = 0.$$
(63)

By rearranging the terms of (63), we obtain the following:

$$\alpha 1^2 p_1^2 + \left(2\sigma_e^2 + \beta_1\right)\alpha_1 p_1 + \beta_1 \sigma_e^2 + \sigma_e^4 - \frac{\lambda_1 \beta_1}{\mu_1} = 0. \quad (64)$$

By solving this equation, the optimal power allocation policy  $p_1$ at the jammer is obtained as  $p_1 \ge 0$ ,

$$p_1^* = \frac{1}{\alpha_1} \left[ \sqrt{\frac{\beta_1^2}{4} + \frac{\lambda_1 \beta_1}{\mu_1}} - \frac{(2\sigma_e^2 + \beta_1)}{2} \right]^+.$$
 (65)

This completes the proof of Lemma 2.

## Proof of Lemma 3

The problem in (21) can be proven to be a convex problem by showing the following function is concave in the interference price  $\mu_1$  for  $p_1^*(>0)$  in (18):

$$f(\mu_1) = \mu_1 \left( \sqrt{c_1 + \frac{c_2}{\mu_1}} - c_0 \right), \tag{66}$$

where  $c_0$ ,  $c_1$  and  $c_2$  are defined in (23). This function can be shown to be concave by finding its second derivative respect to  $\mu_1$  as follows:

$$\frac{\partial f(\mu_1)}{\partial \mu_1} = \left(c_1 + \frac{c_2}{\mu_1}\right)^{\frac{1}{2}} - \frac{c_2}{2\mu_1} \left(c_1 + \frac{c_2}{\mu_1}\right)^{-\frac{1}{2}} - c_0 \quad (67)$$

$$\frac{\partial^2 f(\mu_1)}{\partial \mu_1} = \frac{c_2^2}{2\mu_1} \left(c_1 + \frac{c_2}{\mu_1}\right)^{-\frac{3}{2}} - c_0 \quad (67)$$

$$\frac{\partial^2 f(\mu_1)}{\partial \mu_1^2} = -\frac{c_2^2}{4\mu_1^3} \left(c_1 + \frac{c_2}{\mu_1}\right)^{-2} . \tag{68}$$

Hence the second derivative of  $f(\mu_1)$  with respect to  $\mu_1$  is negative (i.e.,  $\frac{\partial^2 f(\mu_1)}{\partial \mu_1^2} < 0$ ), and  $f(\mu_1)$  is a concave function in  $\mu_1$ . In addition, the optimal interference price  $\mu_1^*$  should satisfy the KKT conditions as follows [44]:

$$\frac{\partial f(\mu_1)}{\partial \mu_1} = \left(c_1 + \frac{c_2}{\mu_1}\right)^{\frac{1}{2}} - \frac{c_2}{2\mu_1} \left(c_1 + \frac{c_2}{\mu_1}\right)^{-\frac{1}{2}} - c_0 = 0.$$
(69)

By rearranging (69), we obtain the following:

$$4c_1 \left(c_0^2 - c_1\right) \mu_1^2 + 4c_2 \left(c_0^2 - c_1\right) \mu_1 - c_2^2 = 0.$$
 (70)

By solving the above equation, the optimal interference price  $\mu_1^*$  to maximize the jammer's revenue is obtained as  $\mu_1 > 0$ ,

$$\mu_1^* = \frac{c_2}{2c_1} \left[ \frac{c_0}{\sqrt{c_0^2 - c_1}} - 1 \right].$$
 (71)

This completes the proof of Lemma 3.

$$\frac{\partial f(\mu_{0})}{\partial \mu_{0}} = \frac{2\lambda_{1}\bar{c}_{1}}{\mu_{0}\bar{c}_{1}+q} - \frac{2\lambda_{1}\bar{c}_{1}\mu_{0}\left(\bar{c}_{1}+\frac{\bar{c}_{1}^{2}\mu_{0}+2\lambda_{1}\bar{c}_{1}}{\mu_{0}\bar{c}_{1}+q}\right)}{(\mu_{0}\bar{c}_{1}+q)^{2}}, \text{ where } q = \sqrt{\mu_{0}\bar{c}_{1}(4\lambda_{1}+\mu_{0}\bar{c}_{1})}, \quad \bar{c}_{1} = \sum_{i=1}^{K}\beta_{i}$$

$$\frac{\partial^{2}f(\mu_{0})}{\partial \mu_{0}^{2}} = \frac{-4\lambda_{1}\bar{c}_{1}\left(\bar{c}_{1}+\frac{\bar{c}_{1}^{2}\mu_{0}+2\lambda_{1}\bar{c}_{1}}{q}\right)}{(\bar{c}_{1}\mu_{0}+q)^{2}} + \frac{4\lambda_{1}\bar{c}_{1}\mu_{0}\left(\bar{c}_{1}+\frac{\bar{c}_{1}^{2}\mu_{0}+2\lambda_{1}\bar{c}_{1}}{q}\right)^{2}}{(\bar{c}_{1}\mu_{0}+q)^{3}} - \frac{2\lambda_{1}\bar{c}_{1}\mu_{0}\left(\frac{\bar{c}_{1}^{2}}{q}-\frac{(\bar{c}_{1}\mu_{0}+2\lambda_{1}\bar{c}_{1})^{2}}{(\bar{c}_{1}\mu_{0}+q)^{2}}\right)}{(\bar{c}_{1}\mu_{0}+q)^{2}} \quad (72)$$

$$\frac{\partial^{2}f(\mu_{0})}{\partial \mu_{0}^{2}} = \frac{-4\lambda_{1}\bar{c}_{1}^{2}q(q+\bar{c}_{1}\mu_{0}+2\lambda_{1})[q^{2}-\bar{c}_{1}\mu_{0}(\bar{c}_{1}\mu_{0}+\lambda_{1})] - 2\lambda_{1}\bar{c}_{1}^{3}\mu_{0}(\bar{c}_{1}\mu_{0}+q)\left[q^{2}-(\bar{c}_{1}\mu_{0}+2\lambda_{1})^{2}\right]}{q^{3}(\bar{c}_{1}\mu_{0}+q)^{3}} \quad (73)$$

By substituting  $q = \sqrt{\mu_0 \bar{c}_1 (4\lambda_1 + \mu_0 \bar{c}_1)}, \Longrightarrow \frac{\partial^2 f(\mu_0)}{\partial \mu_0^2} = \frac{-12\lambda_1^2 \bar{c}_1^3 q \mu_0 (q + \bar{c}_1 \mu_0 + 2\lambda_1) - 8\lambda_1^3 \bar{c}_1^3 \mu_0 (\bar{c}_1 \mu_0 + q)}{q^3 (\bar{c}_1 \mu_0 + q)^3} < 0$  (74)

## APPENDIX D

## Proof of Lemma 6

With the optimal power allocation in (34), the achieved rates of the super-active eavesdroppers (i.e.,  $i \in \mathbb{K}$ ) will be equal as stated in Proposition 2. Hence, the power allocation at the  $i^{\text{th}}$ private jammer can be written as

$$\frac{\beta_i}{\sigma_e^2 + p_i \alpha_i} = \gamma_0, \Longrightarrow p_i = \frac{1}{\alpha i} \left[ \frac{\beta_i}{\gamma_0} - \sigma_e^2 \right]^+.$$
(75)

The original optimization problem in (34) can be formulated in terms of  $\gamma_0$  as follows:

$$\max_{\gamma_0 \ge 0} \quad \lambda_1 \left[ \log(1 + \beta_0) - \log(1 + \gamma_0) \right] \\ - \frac{1}{\gamma_0} \sum_{i=1}^K \mu_i \beta_i + \sigma_e^2 \sum_{i=1}^K \mu_i \\ \triangleq f(\gamma_0).$$
(76)

The optimal  $\gamma_0^*$  should satisfy the KKT conditions and therefore we obtain the following:

$$\frac{\partial f(\gamma_0)}{\partial \gamma_0} = -\frac{\lambda_1}{1+\gamma_0} + \frac{\tau}{\gamma_0^2}, \ \frac{\partial^2 f(\gamma_0)}{\partial \gamma_0^2} = \frac{\lambda_1}{(1+\gamma_0)^2} - \frac{2\tau}{\gamma_0^3},$$
(77)

where  $\tau = \sum_{i=1}^{K} \mu_i \beta_i$ . The function  $f(\gamma_0)$  is concave if the following condition is satisfied:

$$\frac{\gamma_0^3}{(1+\gamma_0)^2} \le \frac{2\tau}{\lambda_1}.$$
(78)

Hence, the optimal  $\gamma_0^*$  can be obtained if  $\lambda_1$  is large enough to satisfy the above condition. This means that the legitimate transmitter should charge the legitimate user a reasonable price to make a profit by introducing interference to the eavesdroppers with the help of the private jammers. However, the optimal  $\gamma_0^*$ should satisfy the KKT conditions  $\frac{\partial f(\gamma_0)}{\partial \gamma_0} = 0$ . The optimal  $\gamma_0^*$ can be obtained by solving the following equation:

$$\lambda_1 \gamma_0^2 - \gamma_0 \sum_{i=1}^K \mu_i \beta_i - \sum_{i=1}^K \mu_i \beta_i = 0,$$
 (79)

and  $\gamma_0 > 0$ ,

$$\gamma_0^* = \frac{\sum_{i=1}^K \mu_i \beta_i + \sqrt{\sum_{i=1}^K \mu_i \beta_i \left(4\lambda_0 + \sum_{i=1}^K \mu_i \beta_i\right)}}{2\lambda_1}.$$
 (80)

Hence the optimal power allocation policy of the  $i^{\rm th}$  can be written as

$$p_i^* = \frac{1}{\alpha i} \left[ \frac{\beta_i}{\gamma_0^*} - \sigma_e^2 \right]^+.$$
(81)

This completes the proof of Lemma 6.

# APPENDIX E

Proof of Lemma 7

We first show that the revenue function of the jammers in (41) is concave in terms of  $\mu_0$  for  $p_i > (0)$  in (37) and then we derive

the optimal interference price  $\mu_0^*$ . The revenue function of the jammers is defined as

$$f(\mu_0) = \frac{2\lambda_1 \mu_0 \bar{c}_1}{\mu_0 \bar{c}_1 + \sqrt{\mu_0 \bar{c}_1 \left(4\lambda_1 + \mu_0 \bar{c}_1\right)}} - K \sigma_e^2 \mu_0, \quad (82)$$

where  $\bar{c}_1 = \sum_{i=1}^{K} \beta_i$ . The concavity of  $f(\mu_0)$  can be proven by finding the second derivative with respect to  $\mu_0$  as in (72), which is at the bottom of the previous page. In order to prove that the function in (82) is concave, we need to show that the second derivative (i.e.,  $\frac{\partial^2 f(\mu_0)}{\partial \mu_0^2}$ ) is negative. This has been proved in (73) and (74) which are at the bottom of the previous page. This confirms that the revenue function of the jammers is concave in  $\mu_0$  and the optimal  $\mu_0^*$  should satisfy the KKT conditions  $\frac{\partial f(\mu_0)}{\partial \mu_0}$ = 0 [44]:

$$\frac{2\lambda_1 \bar{c}_1}{\mu_0 \bar{c}_1 + q} - \frac{2\lambda_1 \bar{c}_1 \mu_0 \left(\bar{c}_1 + \frac{\bar{c}_1^2 \mu_0 + 2\lambda_1 \bar{c}_1}{\mu_0 \bar{c}_1 + q}\right)}{\left(\mu_0 \bar{c}_1 + q\right)^2} = 0, \ (83)$$
$$\mu_0^* = \frac{\frac{1}{2} \left[-4\lambda_1 K \sigma^2 \eta_1 + 2\lambda_1 \sqrt{K \sigma^2 \eta_2 + 4K^2 \sigma^4 \eta_1^2}\right]}{K \sigma^2 \eta_2}.$$

This completes the proof of Lemma 7.

ŀ

#### REFERENCES

- Y. Liang, H. V. Poor, and S. Shamai, "Information theoretic security," Found. Trends Commun. Info. Theory, vol. 5, no. 4/5, pp. 355–580, 2009.
- [2] L. Dong, Z. Han, A. P. Petropulu, and H. V. Poor, "Improving wireless physical layer security via cooperating relays," *IEEE Trans. Signal Process.*, vol. 58, no. 3, pp. 1875–1888, Mar. 2010.
- [3] X. Tang, R. Liu, P. Spasojević, and H. V. Poor, "Interference assisted secret communication," *IEEE Trans. Inf. Theory*, vol. 57, no. 5, pp. 3153–3167, May 2011.
- [4] A. D. Wyner, "The wire-tap channel," Bell Syst. Tech. J., vol. 54, pp. 1355–1387, Jan. 1975.
- [5] I. Csiszár and J. Körner, "Broadcast channels with confidential messages," *IEEE Trans. Inf. Theory*, vol. 24, pp. 339–348, May 1978.
  [6] T. Liu and S. Shamai, "A note on the secrecy capacity of the multiple-
- [6] T. Liu and S. Shamai, "A note on the secrecy capacity of the multipleantenna wiretap channel," *IEEE Trans. Inf. Theory*, vol. 55, no. 6, pp. 2547–2553, Jun. 2009.
- [7] A. Khisti and G. W. Wornell, "Secure transmission with multiple antennas II: The MIMOME wiretap channel," *IEEE Trans. Inf. Theory*, vol. 56, no. 11, pp. 5515–5532, Nov. 2010.
- [8] J. Li and A. P. Petropulu, "On ergodic secrecy rate for Gaussian MISO wiretap channels," *IEEE Trans. Wireless Commun.*, vol. 10, no. 4, pp. 1176–1187, Apr. 2011.
- [9] Q. Li and W.-K. Ma, "Optimal and robust transmit designs for MISO channel secrecy by semidefinite programming," *IEEE Trans. Signal Process.*, vol. 59, no. 8, pp. 3799–3812, Aug. 2011.
- [10] S. A. A. Fakoorian and L. A. Swindlehurst, "Full rank solutions for the MIMO Gaussian wiretap channel with an average power constraint," *IEEE Trans. Signal Process.*, vol. 61, no. 10, pp. 2620–2631, May 2013.
- [11] K. Cumanan, Z. Ding, B. Sharif, G. Y. Tian, and K. K. Leung, "Secrecy rate optimizations for a MIMO secrecy channel with a multiple-antenna eavesdropper," *IEEE Trans. Veh. Technol.*, vol. 63, no. 4, pp. 1678–1690, May 2014.
- [12] W. Xiang, S. L. Goff, M. Johnston, and K. Cumanan, "Signal mapping for bit-interleaved coded modulation schemes to achieve secure communications," *IEEE Wireless Commun. Lett.*, vol. 4, no. 3, pp. 249–252, Jun. 2015.
- [13] Z. Chu, K. Cumanan, M. Xu, and Z. Ding, "Robust secrecy rate optimisations for multiuser multiple-input-single-output channel with deviceto-device communications," *IET Commun.*, vol. 9, no. 3, pp. 396–403, 2015.
- [14] Z. Chu, K. Cumanan, Z. Ding, M. Johnston, and S. L. Goff, "Robust outage secrecy rate optimizations for a MIMO secrecy channel," *IEEE Wireless Commun. Lett.*, vol. 4, no. 1, pp. 86–89, Feb. 2015.

- [15] E. Tekin and A. Yener, "The general Gaussian multiple access and two-way wiretap channels: Achievable rates and cooperative jamming," *IEEE Trans. Inf. Theory*, vol. 54, no. 6, pp. 2735–2751, Jun. 2008.
- [16] J. Huang and L. A. Swindlehurst, "Cooperative jamming for secure communication in MIMO relay networks," *IEEE Trans. Signal Process.*, vol. 59, no. 10, pp. 4871–4884, Oct. 2011.
- [17] Z. Ding, K. K. Leung, D. L. Goeckel, and D. Towsley, "Opportunistic relaying for secrecy communications: Cooperative jamming vs relay chatting," *IEEE Trans. Wireless Commun.*, vol. 29, no. 10, pp. 2067–2076, Jun. 2011.
- [18] G. Zheng, I. Krikidis, J. Li, A. P. Petropulu, and B. Ottersten, "Improving physical layer secrecy using full-duplex jamming receivers," *IEEE Trans. Signal Process.*, vol. 61, no. 20, pp. 4962–4974, Oct. 2013.
- [19] G. Zheng, L. C. Choo, and K. K. Wong, "Optimal cooperative jamming to enhance physical layer security using relays," *IEEE Trans. Signal Process.*, vol. 59, no. 3, pp. 1317–1322, Mar. 2011.
- [20] Z. Chu, K. Cumanan, Z. Ding, M. Johnston, and S. Le Goff, "Secrecy rate optimizations for a MIMO secrecy channel with a cooperative jammer," *IEEE Trans. Veh. Technol.*, vol. 64, no. 5, pp. 1833–1847, May 2015.
- [21] S. Goel and R. Negi, "Guaranteeing secrecy using artificial noise," *IEEE Trans. Wireless Commun.*, vol. 7, no. 6, pp. 2180–2189, Jun. 2008.
- [22] Q. Li and W.-K. Ma, "Spatially selective artificial-noise aided transmit optimization for MISO multi-eves secrecy rate maximization," *IEEE Trans. Signal Process.*, vol. 61, no. 10, pp. 2704–2717, May 2013.
- [23] W.-C. Liao, T.-H. Chang, W.-K. Ma, and C.-Y. Chi, "QoS-based transmit beamforming in the presence of eavesdroppers: An optimized artificialnoise-aided approach," *IEEE Trans. Signal Process.*, vol. 59, no. 3, pp. 1202–1216, Mar. 2011.
- [24] Y. Wu and K. Liu, "An information secrecy game in cognitive radio networks," *IEEE Trans. Inf. Forensics Security*, vol. 6, no. 3, pp. 831–842, Sep. 2011.
- [25] M. Yuksel, X. Liu, and E. Erkip, "A secure communication game with a relay helping the eavesdropper," *IEEE Trans. Inf. Forensics Security*, vol. 6, no. 3, pp. 818–830, Sep. 2011.
- [26] R. Zhang, L. Song, Z. Han, and B. Jiao, "Physical layer security for twoway untrusted relaying with friendly jammers," *IEEE Trans. Veh. Technol.*, vol. 61, no. 8, pp. 3693–3704, Oct. 2012.
- [27] W. Saad, X. Zhou, B. Maham, T. Basar, and H. V. Poor, "Tree formation with physical layer security considerations in wireless multi-hop networks," *IEEE Trans. Wireless Commun.*, vol. 11, no. 11, pp. 3980–3991, Nov. 2012.
- [28] A. Mukherjee and A. Swindlehurst, "Jamming games in the MIMO wiretap channel with an active eavesdropper," *IEEE Trans. Signal Process.*, vol. 61, no. 1, pp. 82–91, Jan. 2013.
- [29] S. A. A. Fakoorian and A. L. Swindlehurst, "Competing for secrecy in the MISO interference channel," *IEEE Trans. Signal Process.*, vol. 61, no. 1, pp. 170–181, Jan. 2013.
- [30] I. Stanojev and A. Yener, "Improving secrecy rate via spectrum leasing for friendly jamming," *IEEE Trans. Wireless Commun.*, vol. 12, no. 1, pp. 134–145, Jan. 2013.
- [31] Q. Li and W. K. Ma, "Multicast secrecy rate maximization for MISO channels with multiple multi-antenna eavesdroppers," in *Proc. IEEE Int. Conf. Commun.*, Kyoto, Japan, pp. 1–5, Jun. 2011.
- [32] A. Shrestha, J. Jung, and K. Kwak, "Robust beamforming in cognitive radio," in *Proc. Int. Symp. Commun. Inf. Technol.*, pp. 814–817, Sep. 2013.
- [33] T. Lin, K.-Z. Huang, and W.-Y. Luo, "A multicarrier-based physical layer security scheme for the multicast systems," in *Proc. Int. Conf. Inf. Sci. Technol.*, pp. 1584–1587, Mar. 2013.
- [34] M. Li, S. Kundu, D. A. Pados, and S. N. Batalama, "Waveform design for secure SISO transmissions and multicasting," *IEEE J. Sel. Areas Commun.*, vol. 31, no. 9, pp. 1864–1874, Sep. 2013.
- [35] X. Liu, F. Gao, G. Wang, and X. Wang, "Joint beamforming and user selection in multicast downlink channel under secrecy-outage constraint," *IEEE Commun. Lett.*, vol. 18, no. 1, pp. 82–85, Jan. 2014.
- [36] P. K. Gopala, L. Lai, and H. E. Gammal, "On the secrecy capacity of fading channels," *IEEE Trans. Inf. Theory*, vol. 54, no. 10, pp. 4687–4698, Oct. 2008.
- [37] S. A. A. Fakoorian and L. A. Swindlehurst, "Solution for the MIMO Gaussian wiretap channel with a cooperative jammer," *IEEE Trans. Signal Process.*, vol. 59, no. 10, pp. 5013–5022, Oct. 2011.

- [38] M. Dehghan, D. Goeckel, M. Ghaderi, and Z. Ding, "Energy efficiency of cooperative jamming strategies in secure wireless networks," *IEEE Trans. Wireless Commun.*, vol. 11, no. 9, pp. 3025–3029, Sep. 2012.
- [39] E. A. Jorswieck and A. Wolf, "Resource allocation for the wire-tap multi-carrier broadcast channel," in *Proc. Int. Conf. Telecommun.*, 2008, pp. 1–6.
- [40] J. Lin, A. P. Petropulu, and S. Weber, "Secrecy rate optimization under cooperation with perfect channel state information," in *Proc. Asilomar Conf. Sign., Syst. Comput.*, pp. 824–828, Nov. 2009.
- [41] J. Yang, I. M. Kim, and D. I. Kim, "Optimal cooperative jamming for multiuser broadcast channel with multiple eavesdroppers," *IEEE Trans. Wireless Commun.*, vol. 12, no. 6, pp. 2840–2852, Jun. 2013.
- [42] N. Sidiropoulos, T. Davidson, and Z.-Q. Luo, "Transmit beamforming for physical-layer multicasting," *IEEE Trans. Signal Process.*, vol. 54, no. 6, pp. 2239–2251, Jun. 2006.
- [43] Z.-Q. Luo, W.-K. Ma, A.-C. So, Y. Ye, and S. Zhang, "Applications of convex optimization in signal processing and digital communication," *IEEE Signal Process. Mag.*, vol. 27, no. 3, pp. 20–34, May 2010.
- [44] S. Boyd and L. Vandenberghe, *Convex Optimization*. Cambridge, U.K.: Cambridge Univ. Press, 2004.



Kanapathippillai Cumanan (M'10) received the B.Sc. (Hons.) degree in electrical and electronic engineering from the University of Peradeniya, Sri Lanka, in 2006, and the Ph.D. degree in signal processing for wireless communications from Loughborough University, Loughborough, U.K., in 2009.

He is currently a Lecturer in the Department of Electronics, University of York, U.K. He was with the School of Electronic, Electrical and System Engineering, Loughborough University, U.K. He was a Teaching Assistant with the Department of Electri-

cal and Electronic Engineering, University of Peradeniya, Sri Lanka, in 2006. In 2011, he was an Academic Visitor with the Department of Electrical and Computer Engineering, National University of Singapore, Singapore. He was a Research Associate with the School of Electrical and Electronic Engineering, Newcastle University, U.K., from 2012 to 2014. His research interests include physical layer security, cognitive radio networks, relay networks, convex optimization techniques, and resource allocation techniques.

Dr. Cumanan received the Overseas Research Student Award Scheme from Cardiff University, Wales, U.K., where he was a Research Student from 2006 to 2007.



Zhiguo Ding (S'03–M'05–SM'15) received the B.Eng. degree in electrical engineering from the Beijing University of Posts and Telecommunications, in 2000, and the Ph.D. degree in electrical engineering from Imperial College London, London, U.K., in 2005. From 2005 to 2014, he was with Queens University Belfast, Imperial College, and Newcastle University. Since 2014, he has been with Lancaster University as a Chair Professor. From 2012 to 2016, he was also with Princeton University as an Academic Visitor. His research interests inlcude

5G networks, game theory, cooperative and energy harvesting networks, and statistical signal processing. He serves as an Editor of the IEEE TRANS-ACTIONS ON COMMUNICATIONS, the IEEE TRANSACTIONS ON VEHICULAR NETWORKS, the IEEE WIRELESS COMMUNICATION LETTERS, the IEEE COM-MUNICATION LETTERS, and the *Journal of Wireless Communications and Mobile Computing*. He received the best paper award at the IET Communcation Conference on Wireless, Mobile and Computing, 2009, the IEEE Communication Letter Exemplary Reviewer Award, 2012, and the EU Marie Curie Fellowship 2012–2014.



**Mai Xu** (M'10) received the B.S. degree from Beihang University, Beijing, China, in 2003, M.S. degree from Tsinghua University, Beijing, China, in 2006 and Ph.D degree from Imperial College London, London, U.K., in 2010. From 2010 to 2012, he was working as a Research Fellow in the Electrical Engineering Department, Tsinghua University. Since January 2013, he has been with Beihang University as an Associate Professor. During 2014 to 2015, he was a Visiting Researcher of MSRA. His research interests mainly include visual communication and

image processing. He has published more than 50 technical papers in international journals and conference proceedings. He received the best paper awards of two IEEE conferences.



H. Vincent Poor (S'72–M'77–SM'82–F'87) received the Ph.D. degree in EECS from Princeton University, Princeton, NJ, USA, in 1977. From 1977 until 1990, he was on the faculty of the University of Illinois at Urbana-Champaign. Since 1990, he has been on the faculty at Princeton, where he is the Michael Henry Strater University Professor of Electrical Engineering. From 2006 till 2016, he served as the Dean of Princeton's School of Engineering and Applied Science. His research interests inlcude the areas of statistical signal processing, stochastic anal-

ysis and information theory, and their applications in wireless networks and related fields. Among his publications in these areas is the recent book *Mechanisms and Games for Dynamic Spectrum Allocation* (Cambridge University Press, 2014).

Dr. Poor is a Member of the National Academy of Engineering and the National Academy of Sciences, and a foreign Member of the Royal Society. He is also a Fellow of the American Academy of Arts and Sciences and the National Academy of Inventors, and of other national and international academies. He received the Technical Achievement and Society Awards of the IEEE Signal Processing Society in 2007 and 2011, respectively. Recent recognition of his work includes the 2014 URSI Booker Gold Medal, the 2015 EURASIP Athanasios Papoulis Award, the 2016 John Fritz Medal, and honorary doctorates from Aalborg University, Aalto University, HKUST and the University of Edinburgh.